

Clavinova®

CLP-370/340/S308/S306 バージョン 1.60 追加機能説明書

無線LAN をお使いの方へ

CLP-370/340/S308/S306のバージョンアップにともない、無線LANの設定方法が追加されました。

■ 無線LAN画面に追加/変更された機能

● 設定方法の追加

WPSプッシュボタン方式が追加され、無線LANの設定が簡単にできるようになりました。

NOTE

WPSプッシュボタン方式を使わない場合の具体的な設定方法については、下記URLをご確認ください。
<http://jp.yamaha.com/products/musical-instruments/keyboards/net/idc/clp/connection/>

● セキュリティの強化

無線LANのセキュリティ方式WPA/WPA2に対応しました。従来採用されていたWEPより強固な方式です。

強化されたセキュリティの種別は下記になります。

WPA-PSK (TKIP) WPA-PSK (AES) WPA2-PSK (TKIP) WPA2-PSK (AES)

USB無線LANアダプター (DHCP使用)をお使いの場合のみ、上記のインターネット設定方法をご利用できます。CLP-370/340/330/S308/S306取扱説明書(45ページ)、またはCLP-370/340/330取扱説明書(44ページ)の「インターネットダイレクト接続機能」と、本書を一緒にお読みください。

NOTE

WPAおよびWPSプッシュボタン方式は、一部のUSB無線LANアダプターには対応していません。使用できるUSB無線LANアダプターについて詳しくは、下記のUSBデバイス動作確認済みリストでご確認ください。
<http://jp.yamaha.com/products/musical-instruments/keyboards/support/usb/>

NOTE

WPSプッシュボタン方式を使って無線LANを設定するには、アクセスポイントがWPSプッシュボタン方式に対応している必要があります。アクセスポイントの設定の確認/変更については、お使いの無線LANルーター (アクセスポイント)の取扱説明書をご覧ください。

NOTE

この楽器のWPSはPINコード方式には対応していません。

インターネット設定(WPSプッシュボタン方式に関する設定)について

はじめてインターネットダイレクト接続機能を利用するときには、楽器上でインターネット設定(無線LAN)を行ない、その設定を保存します。ここではUSB無線LANアダプター (DHCP使用)をお使いの場合のインターネット設定を説明します。

WPSプッシュボタン方式を使って設定する

お使いの無線LANルーター (アクセスポイント)が、WPSプッシュボタン方式に対応している場合、自動的にインターネット設定を行なうことができます。

1. ファンクションモードに入る

[TEMPO/FUNCTION]ボタンを押してファンクションモードに入ります。

2. [F9.y] (CLP-370/340)、[F8.y] (CLP-S308/S306)を表示させる

[TEMPO/FUNCTION ▼▲]ボタンを押して [F9.y] (CLP-370/340)、または [F8.y] (CLP-S308/S306)を表示させます。

3. [F9.] (CLP-370/340)、[F8.] (CLP-S308/S306)に続く小項目の設定に入る

[+/YES] ボタンを押して小項目の設定に入ります。

4. [F9.] (CLP-370/340)、[F8.] (CLP-S308/S306)に続く小項目を設定する

[TEMPO/FUNCTION ▼▲] ボタンを押して [F9.8] (CLP-370/340)、[F8.8] (CLP-S308/S306)を表示させます。

5. WPSプッシュボタン方式を使った設定に入る

[+/YES]または[-/NO]ボタンを押してWPSプッシュボタン方式を使った設定に入ります。

6. 2分以内にお使いのアクセスポイントのWPSボタンを押す

SSID、チャンネル、セキュリティ、キーの設定が自動的に入力されます。WPSプッシュボタン方式を使った設定が実行され「End」が表示されます。設定が正常終了した場合、設定は自動的に保存されます。この際、設定として保存されるのは無線LANに関する項目(SSID、チャンネル、セキュリティ種別、キー)で他の項目の値は初期化されます。

これで、WPSプッシュボタン方式を使った設定は完了です。

7. ファンクションの操作を終了する

[+/YES]または[-/NO]ボタンを押します。

本書をお手持ちのCLP-370/340/330/S308/S306取扱説明書では60ページ、CLP-370/340/330取扱説明書では59ページの手順5と同様に[TEMPO/FUNCTION]ボタンを押してファンクションモードから抜けます。

USB無線LANアダプター (DHCP使用)をお使いでない場合の設定方法については、下記URLをご確認ください。

<http://jp.yamaha.com/products/musical-instruments/keyboards/net/idc/clp/connection/>

デモ曲モード、曲の再生中、録音中、ファイル操作中はファンクションモードに入れません。

アクセスポイントの設定の確認/変更については、お使いの無線LANルーター (アクセスポイント)の取扱説明書をご覧ください。

設定が正常に完了しなかった場合は、ディスプレイに「Err」とエラーコードが交互に表示されません。この状態から元の状態に戻すには[-/NO]ボタン、または、[+/YES]ボタンを押します。

エラーコード

エラーコードの内容については、インターネット上のウェブページ

<http://jp.yamaha.com/products/musical-instruments/keyboards/net/idc/clp/troubleshoot01/>で、ご確認ください。

より詳しい設定方法については、下記URLをご確認ください。

<http://jp.yamaha.com/products/musical-instruments/keyboards/net/idc/clp/connection/>

BSDライセンスソフトウェアの利用に関するお知らせ

本製品はソフトウェアの一部にBSDライセンスに従ったソフトウェアを利用しています。BSDライセンスとは、無保証の旨の明記、著作権表示、ライセンス条文一覧の表示を条件としてプログラムの再頒布が許諾されるソフトウェアのライセンス形式です。

下記の内容は、上記ライセンス条件にもとづき表示されるものであり、お客様の使用制限等を規定するものではありません。

記

WPA Supplicant

Copyright © 2003-2009, Jouni Malinen <j@w1.fi> and contributors
All Rights Reserved.

This program is dual-licensed under both the GPL version 2 and BSD license. Either license may be used at your option.

License

Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:

1. Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimer.
2. Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials provided with the distribution.
3. Neither the name(s) of the above-listed copyright holder(s) nor the names of its contributors may be used to endorse or promote products derived from this software without specific prior written permission.

THIS SOFTWARE IS PROVIDED BY THE COPYRIGHT HOLDERS AND CONTRIBUTORS "AS IS" AND ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE COPYRIGHT OWNER OR CONTRIBUTORS BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO,

PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

XySSL

Copyright © 2006-2008, Christophe Devine.
All rights reserved.

Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:

- * Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimer.
- * Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials provided with the distribution.
- * Neither the name of XySSL nor the names of its contributors may be used to endorse or promote products derived from this software without specific prior written permission.

THIS SOFTWARE IS PROVIDED BY THE COPYRIGHT HOLDERS AND CONTRIBUTORS "AS IS" AND ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE COPYRIGHT OWNER OR CONTRIBUTORS BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.